

PTO/PCT Rec'd 24 OCT 2000

PATENT
0054-0219P

IN THE U.S. PATENT AND TRADEMARK OFFICE

Applicant: Steve Duncan
Appl. No.: 09/642,154 Group:
Filed: August 21, 2000 Examiner:
For: OFDM FRAME SYNCHRONISATION

L E T T E R

Assistant Commissioner for Patents
Washington, DC 20231

October 24, 2000

Sir:

Under the provisions of 35 U.S.C. § 119 and 37 C.F.R. § 1.55(a), the applicant(s) hereby claim(s) the right of priority based on the following application(s):

<u>Country</u>	<u>Application No.</u>	<u>Filed</u>
UNITED KINGDOM	9920446.3	August 27, 1999

A certified copy of the above-noted application(s) is(are) attached hereto.

If necessary, the Commissioner is hereby authorized in this, concurrent, and future replies, to charge payment or credit any overpayment to Deposit Account No. 02-2448 for any additional fee required under 37 C.F.R. §§ 1.16 or 1.17; particularly, extension of time fees.

Respectfully submitted,

BIRCH, STEWART, KOLASCH & BIRCH, LLP

By 

Michael K. Mutter, #29,680

MKM/jms
0054-0219P

P.O. Box 747
Falls Church, VA 22040-0747
(703) 205-8000

Attachment



The
Patent
Office

Serial No: 09/642,154
Docket: 0054-0219P
Filed: August 21, 2000
Inventor: STEVE DUNCAN
BIRCH, STEWART, KOLASCH
& BIRCH, LLP



INVESTOR IN PEOPLE

#17

The Patent Office
Concept House
Cardiff Road
Newport
South Wales
NP10 8QQ


I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.

I also certify that the attached copy of the request for grant of a Patent (Form 1/77) bears an amendment, effected by this office, following a request by the applicant and agreed to by the Comptroller-General.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.



Signed

JEvens.

Dated 07 August 2000

THIS PAGE BLANK (USPTO)



Request for grant of a patent

(See the notes on the back of this form. You can also get an explanatory leaflet from the Patent Office to help you fill in this form)



The Patent Office

Cardiff Road
Newport
Gwent NP9 1RH

1. Your reference	J00041703GB		
2. Patent application number (The Patent Office will fill in this part)	9920446.3		
3. Full name, address and postcode of the or of each applicant (underline all surnames)	Mitsubishi Electric Information Technology Centre Europe B.V. F01/7700 0.00 - 9920446.3 20 Frederick Sanger Road The Surrey Research Park Guildford, Surrey GU2 5YD United Kingdom		
Patents ADP number (if you know it)	0754274900!		
If the applicant is a corporate body, give the country/state of its incorporation	United Kingdom ALL 30 May 00 UK	NETHERLANDS	(99)
4. Title of the invention	OFDM FRAME SYNCHRONISATION		
5. Name of your agent (if you have one)	R.G.C. JENKINS & CO.		
"Address for service" in the United Kingdom to which all correspondence should be sent (including the postcode)	26 Caxton Street London SW1H 0RJ		
Patents ADP number (if you know it)	950001 ✓		
6. If you are declaring priority from one or more earlier patent applications, give the country and the date of filing of the or of each of these earlier applications (and if you know it) the or each application number	Country	Priority application number (if you know it)	Date of filing (day / month / year)
7. If this application is divided or otherwise derived from an earlier UK application, give the number and the filing date of the earlier application	Number of earlier application	Date of filing (day / month / year)	
8. Is a statement of inventorship and of right to grant of a patent required in support of this request (Answer 'Yes' if: a) any applicant named in part 3 is not an inventor, or b) there is an inventor who is not named as an applicant, or c) any named applicant is a corporate body. See note (d))	Yes		


9. Enter the number of sheets for any of the following items you are filing with this form.
Do not count copies of the same document

Continuation sheets of this form

Description 9

Claim(s) 3


Abstract 1

Drawing(s) 3 

10. If you are also filing any of the following, state how many against each item.

Priority documents

Translation of priority documents

Statement of inventorship and right to grant of a patent (Patents Form 7/77) 

Request for preliminary examination and search (Patents Form 9/77) 1

Request for substantive examination (Patents Form 10/77)

Any other documents
(please specify)

11. I/We request the grant of a patent on the basis of this application.

Signature

Date 27 August, 1999

R.G.C. JENKINS & CO

12. Name and daytime telephone number of person to contact in the United Kingdom

S. D. Burke 0171-931-7141

Warning

After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction has been revoked.

Notes

- If you need help to fill in this form or you have any questions, please contact the Patent Office on 0645 500505.
- Write your answers in capital letters using black ink or you may type them.
- If there is not enough space for all relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.
- If you have answered 'Yes' Patents Form 7/77 will need to be filed.
- Once you have filled in the form you must remember to sign and date it.
- For details of the fee and ways to pay, please contact the Patent Office.

OFDM FRAME SYNCHRONISATION

This invention relates to OFDM modulation. It is particularly concerned with the generation of a synchronisation pulse representing an OFDM symbol boundary, for example for use in Fourier Transform demodulation.

OFDM systems are well known. Various techniques have been used for synchronisation of OFDM receivers. Some of these techniques require transmission of a special synchronisation signal. Other techniques rely on a standard OFDM signal, in which a complete symbol comprises a "useful part" and a "guard space", the guard space sometimes being referred to as a guard interval, cyclic extension or cyclic prefix.

The guard space precedes the useful part of the symbol and contains a repeat of the data at the end of the useful part. (This is equivalent to having a guard space after the useful part, containing data which is the same as that at the beginning of the useful part.)

Synchronisation techniques which rely upon the duplicated data in the guard space generally operate by performing a cross correlation between complex samples spaced apart by the length of the useful part of the symbol. This generates a timing pulse which is used in Fourier Transformation of the received signal. The timing of the pulse is such that the Fourier Transform window contains only data from a single symbol.

If the timing is incorrect, inter-symbol-interference (ISI) occurs. However, the use of the guard space allows a certain amount of variation in the timing of the pulse while still avoiding ISI. The guard space should be longer than the longest expected spread of delays amongst signals received via different paths. The guard space is relatively small compared with the useful part of the signal; typically, the guard space may contain $N_u/32$, $N_u/16$, $N_u/8$ or $N_u/4$ samples, where N_u is the number of samples in the useful part of the symbol.

It would be desirable to provide a simpler and less expensive technique for synchronisation, and preferably one which can produce more accurate results.

Aspects of the present invention are set out in the accompanying claims.

According to a further aspect, a synchronisation pulse for a Fourier Transform demodulator is generated by taking absolute values of complex samples of an OFDM symbol, determining the difference between absolute values which are separated by the length of the useful part of the signal, and generating the synchronisation pulse in response to determining the time at which there is a substantial increase in the difference value.

The invention also extends to apparatus for generating such a synchronisation pulse, and to a method and an apparatus for receiving an OFDM signal using such techniques.

Using the method of the invention, the difference between the absolute values of the complex values will be very small when those complex values are equal. Thus, this difference will remain small whenever the samples in a guard space are subtracted from the corresponding values within the useful part of the symbol. When the values cease to be small, this represents the end of the symbol, and this point can be used to allow an FFT demodulator window to be aligned with the OFDM symbol.

It is found that, for example because of slight drift in the local oscillator, the complex samples of an OFDM signal can suffer different phase rotations within the period of a single symbol. Thus, although nominally the data in a guard space should correspond to part of the data in the useful part of the symbol, the actual complex values derived from the signal may differ because of this phase rotation. However, by taking the absolute values of the complex samples, such differences are reduced substantially. Furthermore, because the system handles real, rather than complex, values, data storage requirements are reduced. The complexities and inaccuracies associated with multipliers can also be avoided. The arrangement can also produce better accuracy than these systems which rely on integrating the output of a cross-correlator, and better acquisition times than prior art systems relying on phase locked loops (PLL's).

Preferably, the difference values are integrated over a number of symbols. Preferably this is achieved using an infinite impulse response (IIR) filter.

An arrangement embodying the arrangement will now be described by way of example with reference to the accompanying drawings, in which:

Figure 1 is a block diagram of an OFDM receiver;

Figure 2 represents an OFDM signal;

Figure 3 schematically illustrates the processing carried out in a Fourier Transform synchroniser circuit of a receiver according to the present invention;

Figure 4 shows a typical trace of an absolute difference signal arising in the synchronising circuit of Figure 3; and

Figure 5 is a typical output from a rising edge detector of the synchronising circuit.

Referring to Figure 1, an OFDM receiver 2 comprises an antenna 4 which receives a signal and presents it to a down-converter 6 which converts the RF signal to an IF signal. This is then converted into a baseband signal by an IF-to-baseband converter 8. This produces at its output complex samples of each transmitted OFDM symbol. These complex samples are digitised by an analog-to-digital (A/D) converter 10, and delivered to a Fast Fourier Transform (FFT) circuit 14. The FFT circuit 14 converts the samples from the time domain to the frequency domain, and the symbol data at the output is

provided to a channel estimator and corrector 16 and a decoder 17. If desired, the complex samples from the A/D converter 10 and/or a signal from the channel estimator and corrector 16 may also be delivered to a frequency synchronisation circuit 18, which is used to control the local oscillator frequencies used by the down converter 6 and the IF-to-baseband converter 8; however, it is also possible to implement the receiver without requiring such feedback.

The complex samples are also delivered to a symbol synchronisation circuit 20, which generates a synchronisation pulse for use by the Fast Fourier Transform (FFT) circuit 14. The FFT circuit 14 requires the synchronisation pulse so that each transformation operation is aligned with the start of the OFDM symbol.

The circuit described so far is known from the prior art. The present invention is directed to a novel and inventive technique for use in the symbol synchronisation circuit 12.

Referring to Figure 2, it is assumed that an OFDM symbol consists of $N_u + N_g$ samples, representing N_u samples in the useful part U of the signal, preceded by N_g samples in the guard space G. The N_g samples in the guard space G contain the same data as the last N_g samples of the useful part U of the symbol (as indicated, in respect of one of the symbols, by hatching).

Figure 3 is a schematic block diagram representing the functions performed by the circuit 20.

The complex samples from the IF-to-baseband converter 8 are converted into absolute values by an absolute value converter 21. These output values are delivered to a subtractor 22 and to delay circuit 24, which delays the values by an amount corresponding to the length of the useful part U of the OFDM symbol. Accordingly, the delay circuit 24 delays the absolute values by a period corresponding to N_u samples. The subtractor 22 subtracts the delayed absolute values from the non-delayed values received from the absolute value converter 21. The resultant difference value is converted into an absolute value by a second absolute value converter 26. The output of the absolute value converter 26 will therefore be substantially zero during the period that the last N_g samples contained in the useful part U are present at the input of the absolute value converter 21, because at this time the subtractor will be receiving those samples at its positive input and, at its negative input, samples of equal value derived from the guard space G. At other times, the output of the absolute value converter 26 would adopt values determined by the correlation, if any, between data in successive symbols, but in practice this would be essentially random.

The output of the absolute value converter 26 will therefore comprise successive absolute difference values, each associated with a respective sample of the OFDM symbol. These difference values are then passed to an integrating circuit 28, which serves to integrate each absolute difference value over a number of symbols.

This is achieved by multiplying each difference value by a factor $G1$ in a multiplier 30, the output of which is delivered to a positive input of a summing circuit 32. The output of the summing circuit is sent to a delay circuit formed by a first-in, first-out (FIFO) memory 34 which serves to delay each of its input signals by a period corresponding to an entire OFDM symbol, i.e. $N_u + N_g$ samples. The output of the delay circuit 34 is delivered to a positive input of the summer 32, and also to a further multiplying circuit 36 which multiplies the output by $G2$. The resultant of this is sent to a negative input of the summer 32.

As a consequence of this arrangement, the output of the summer comprises successive samples $S(n,m)$, where n represents the number of the sample within the OFDM symbol and m represents the symbol, and wherein:

$$S(n,m) = G1 (V(n,m)) + (1-G2)S(n,m-1)$$

and wherein $V(n,m)$ represents the absolute value for the sample position n of symbol m .

A typical output of the integrating circuit 28 is shown in Figure 4. It will be noted that there are spaced periods in which the output is substantially zero, corresponding to the periods in which the last N_g symbols of the useful part U are present at the input of the absolute value converter 21. These periods are separated by intervals in which there is a substantial amount of random data. The distinction between the two types of intervals is enhanced by integration over a number of symbol periods.

The output of the summing circuit 32 is delivered to a rising edge detector 38, a typical output of which is shown in Figure 5. This output is delivered to a peak detector 40, which detects the trailing edge of each of the periods corresponding to the presence of the guard interval at the output of the delay circuit 34. The peak detector 40 outputs a logic high signal precisely once per OFDM frame, which is used as the sync pulse denoting the end of the OFDM symbol FFT window.

In the preferred embodiment, the delay circuit 34 comprises a plurality of memory elements or registers arranged in a FIFO array. Instead of taking the output of summer 32 for processing in real time, the contents of the registers in the delay circuit 34 can be processed to determine the register (and hence the sample) corresponding to the end of the OFDM symbol.

Whichever arrangement is used, the edge detection and peak detection can be achieved using either hardware or software. The rising edge detector 38 may be implemented by a FIR filter, which may have variable coefficients which are altered following switch on or re-tuning to speed up the locking on to the signal. For example, the FIR filter may be arranged to subtract from the value of the latest sample the values of the preceding n samples. This will give a significant positive value only at the end of the symbol, when the difference between the absolute values ceases to be zero. The value n may be altered not only when acquiring a signal, but also in dependence on, for example, the risk of multi-path interference; when there is significant multi-

path interference, there will be noise in the initial part of the period where the difference between the absolute values ought ideally to be zero, so a smaller value for n would be appropriate.

The invention has been described in the context of an OFDM receiver,
5 in which the synchronisation pulse is used to define the window of samples on which a Fast Fourier Transformation is performed. However, the invention is also useful in other circumstances in which there is a need for a synchronisation pulse representing the symbol boundaries; for example, such a pulse would be valuable in a repeater where full FFT demodulation is not
10 performed.

The functional elements described herein can be implemented either in dedicated hardware or in software.

CLAIMS:

1. A method of generating a synchronisation pulse representing a symbol boundary in an OFDM signal comprising useful symbol periods separated by guard spaces, with data in each guard space corresponding to
5 part of the data in a respective useful period, the method comprising the step of deriving the difference between absolute values of samples of the OFDM signal separated by a period corresponding to the useful symbol period, and generating the synchronisation pulse in response to a substantial change in the difference values.
10
2. A method as claimed in claim 1, wherein the difference values represent integrated values obtained over a plurality of symbol periods.
3. A method as claimed in claim 2, wherein an infinite impulse
15 response filter is used for producing the integrated values.
4. A method as claimed in any preceding claim, including an edge detector for detecting substantial changes in the difference values.
- 20 5. A method as claimed in claim 4, wherein the edge detector comprises a filter.

6. A method as claimed in claim 5, wherein the filter has variable coefficient.

7. A method as claimed in claim 5 or claim 6, wherein the filter is a finite impulse response filter.

8. A method of generating a synchronisation pulse substantially as herein described with reference the accompanying drawings.

9. Apparatus for generating a synchronisation pulse, the apparatus being arranged to operate in accordance with a method of any preceding claim.

10. A method of receiving an OFDM signal comprising demodulating the signal in order to produce complex samples of transmitted OFDM symbols, and applying a Fourier Transform to the complex samples, the method further including the step of synchronising the Fourier Transform window with the OFDM symbols using a synchronisation pulse generated by a method according to any one of claims 1 to 8.

11. An OFDM receiver arranged to operate in accordance with the method of claim 10.

12. An OFDM receiver substantially as herein described with reference to the accompanying drawings.



ABSTRACT

FFT demodulation of OFDM symbols is achieved using a frame
synchronisation pulse generated by deriving absolute values of successive
5 complex samples of the OFDM symbol, determining the difference between
such values and other values separated therefrom by a period representing the
useful part of the OFDM symbol, integrating the difference values over a
plurality of symbols and determining the sample position representing the
point at which the integrated difference values substantially change.

10


[Figure 3 is to accompany the abstract]

THIS PAGE BLANK (USPTO)





THIS PAGE BLANK (USPTO)

FIG. 3



THIS PAGE BLANK (USPTO)

FIG. 4FIG. 5

THIS PAGE BLANK (USPTO)